

D-link Switch: DGS-3627 Firmware: R1 MIB File: V1

How to use NET-SNMP – IGMP Management (DGS-3627)

The Location of IGMP Management OID

The screenshot shows the D-Link MIB Compiler interface. The left pane displays a list of MIB files and their Root IDs. The right pane shows the hierarchical tree structure of the selected MIB file.

| MIB | Root ID |
|---------------------------|----------------------------------|
| DGS3612G-L2MGMT-MIB | 1.3.6.1.4.1.171.11.70.9.2 |
| DGS3627G-L2MGMT-MIB | 1.3.6.1.4.1.171.11.70.8.2 |
| DGS3627-L2MGMT-MIB | 1.3.6.1.4.1.171.11.70.6.2 |
| DGS3650-L2MGMT-MIB | 1.3.6.1.4.1.171.11.70.5.2 |
| DISMAN-PING-MIB | 1.3.6.1.2.1.80 |
| DISMAN-TRACEROUTE-MIB | 1.3.6.1.2.1.81 |
| DLINK-AGENT-MIB | 1.3.6.1.4.1.171.12.1 |
| DLINK-AUTH-MIB | 1.3.6.1.4.1.171.12.3 |
| DLINK-EQUIPMENT-MIB | 1.3.6.1.4.1.171.12.11 |
| DLINK-ID-REC-MIB | 1.3.6.1.4.1.171 |
| Dot1xMgmt-MIB | 1.3.6.1.4.1.171.12.30 |
| Double-VLAN-MIB | 1.3.6.1.4.1.171.12.28 |
| DVMRP-MIB | 1.3.6.1.3.62 |
| DXS3326GSR-SWL2MGMT-MIB | 1.3.6.1.4.1.171.11.59.7.2 |
| DXS3326GSR-SWL3MGMT-MIB | 1.3.6.1.4.1.171.11.59.7.3 |
| DXS3350SR-SWL2MGMT-MIB | 1.3.6.1.4.1.171.11.59.8.2 |
| DXS3350SR-SWL3MGMT-MIB | 1.3.6.1.4.1.171.11.59.8.3 |
| ENTITY-MIB | 1.3.6.1.2.1.47 |
| EQUIPMENT-MIB | 1.3.6.1.4.1.171.12.11 |
| EtherLike-MIB | 1.3.6.1.2.1.10.7 |
| FILE-SYSTEM-MIB | 1.3.6.1.4.1.171.12.14 |
| IANAifType-MIB | 1.3.6.1.2.1.30 |
| IANA-RTPROTO-MIB | 1.3.6.1.2.1.84 |
| IEEE8021-PAE-MIB | 1.0.8802.1.1 |
| IF-MIB | 1.3.6.1.2.1.31 |
| IGMP-STD-MIB | 1.3.6.1.2.1.85 |
| IGMPV3-MIB | 1.3.6.1.4.1.171.12.18 |
| IP-MAC-BIND-MIB | 1.3.6.1.4.1.171.12.23 |
| IPMROUTE-STD-MIB | 1.3.6.1.2.1.83 |
| IPV6-STATIC-ROUTE-MIB | 1.3.6.1.4.1.171.12.26 |

The right pane shows the tree structure of the selected MIB file. The tree is as follows:

- swL2MirrorPortSourceEgress
- swL2MirrorPortState
- swL2IGMPMgmt (highlighted in red)
- swL2IGMPMaxSupportedVlans
- swL2IGMPMaxIpGroupNumPerVlan
- swL2IGMPCtrlTable
 - swL2IGMPCtrlEntry
 - swL2IGMPCtrlVid
 - swL2IGMPQueryInterval
 - swL2IGMPMaxResponseTime
 - swL2IGMPRobustness
 - swL2IGMPLastMemberQueryInterval
 - swL2IGMPHostTimeout
 - swL2IGMPRouteTimeout
 - swL2IGMPLeaveTimer
 - swL2IGMPQueryState
 - swL2IGMPCurrentState
 - swL2IGMPCtrlState
 - swL2IGMPFastLeaveState
- swL2IGMPInfoTable
 - swL2IGMPInfoEntry
 - swL2IGMPVid
 - swL2IGMPGroupIpAddr
 - swL2IGMPMacAddr
 - swL2IGMPPortMap
 - swL2IGMPIpGroupReportCount
- swL2IGMPRouterPortsTable
 - swL2IGMPRouterPortsEntry
 - swL2IGMPRouterPortsVid
 - swL2IGMPRouterStaticPortList
 - swL2IGMPRouterDynamicPortList
 - swL2IGMPRouterForbiddenPortList
- swL2TrafficSegMgmt

MIB File: DGS3627-L2MGMT-MIB

OID: 1.3.6.1.4.1.171.11.70.6.2.11

D-link Switch: DGS-3627 **Firmware:** R1 **MIB File:** V1

Show IGMP Max Supported VLANs

:: Command ::

```
snmpget -v2c -c public 192.168.0.1 1.3.6.1.4.1.171.11.70.6.2.11.1.0
```

| | |
|-----------------|--|
| Object name | swL2IGMPMaxSupportedVlans |
| Object ID | 1.3.6.1.4.1.171.11.70.6.2.11.1 |
| Module | DGS3627-L2MGMT-MIB |
| Base syntax | Integer |
| Composed syntax | INTEGER |
| Access | Read-Only |
| Status | Current |
| Value list | 1 : 0..65535 |
| Parent node | swL2IGMPMgmt |
| First child | None |
| Description | Maximum number of Vlans in the layer 2 IGMP control table (swL2IGMPCtrlTable). |

Show IGMP Max IP Group Number Per VLAN

:: Command ::

```
snmpget -v2c -c public 192.168.0.1 1.3.6.1.4.1.171.11.70.6.2.11.2.0
```

| | |
|-----------------|---|
| Object name | swL2IGMPMaxIpGroupNumPerVlan |
| Object ID | 1.3.6.1.4.1.171.11.70.6.2.11.2 |
| Module | DGS3627-L2MGMT-MIB |
| Base syntax | Integer |
| Composed syntax | INTEGER |
| Access | Read-Only |
| Status | Current |
| Value list | 1 : 0..65535 |
| Parent node | swL2IGMPMgmt |
| First child | None |
| Description | Maximum number of multicast ip group per Vlan in the layer 2 IGMP information table (swL2IGMPQueryInfoTable). |

IGMP Control Table

| | |
|-------------|---|
| Object name | swL2IGMPCtrlTable |
| Object ID | 1.3.6.1.4.1.171.11.70.6.2.11.3 |
| Module | DGS3627-L2MGMT-MIB |
| Base syntax | Sequence Of swL2IGMPCtrlEntry |
| Access | Not_Accessible |
| Status | Current |
| Sequence | 1:swL2IGMPCtrlVid - Integer 2:swL2IGMPQueryInterval - Integer 3:swL2IGMPMaxResponseTime - Integer 4:swL2IGMPRobustness - Integer 5:swL2IGMPLastMemberQueryInterval - Integer 6:swL2IGMPHostTimeout - Integer 7:swL2IGMPRouteTimeout - Integer 8:swL2IGMPLeaveTimer - Integer 9:swL2IGMPQueryState - Integer 10:swL2IGMPCurrentState - Integer 11:swL2IGMPCtrlState - Integer 12:swL2IGMPFastLeaveState - Integer |
| Parent node | swL2IGMPMgmt |
| First child | swL2IGMPCtrlEntry |
| Description | The table controls the Vlan's IGMP function. Its scale depends on current VLAN state (swL2VlanInfoStatus). If VLAN is disabled mode, there is only one entry in the table, with index 1. If VLAN is in Port-Base or 802.1q mode, the number of entries can be up to 12, with index range from 1 to 12. |

D-link Switch: DGS-3627 Firmware: R1 MIB File: V1

Show Layer2 IGMP Control VID

:: Command ::

```
snmpwalk -v2c -c public 192.168.0.1 1.3.6.1.4.1.171.11.70.6.2.11.3.1.1
```

| | |
|-----------------|--|
| Object name | swL2IGMPCtrlVid |
| Object ID | 1.3.6.1.4.1.171.11.70.6.2.11.3.1.1 |
| Module | DGS3627-L2MGMT-MIB |
| Base syntax | Integer |
| Composed syntax | INTEGER |
| Access | Read-Only |
| Status | Current |
| Value list | 1 : 0..65535 |
| Parent node | swL2IGMPCtrlEntry |
| First child | None |
| Description | This object indicates the IGMP control entry's VLAN id. If VLAN is disabled, the Vid is always 0 and cannot be changed by management users. If VLAN is in Port-Base mode, the Vid is arranged from 1 to 12, fixed form. If VLAN is in 802.1q mode, the Vid setting can vary from 1 to 4094 by management user, and the Vid in each entry must be unique in the IGMP Control Table. |

Show Layer2 IGMP Query Interval

:: Command ::

```
snmpwalk -v2c -c public 192.168.0.1 1.3.6.1.4.1.171.11.70.6.2.11.3.1.2
```

| | |
|-----------------|--|
| Object name | swL2IGMPQueryInterval |
| Object ID | 1.3.6.1.4.1.171.11.70.6.2.11.3.1.2 |
| Module | DGS3627-L2MGMT-MIB |
| Base syntax | Integer |
| Composed syntax | INTEGER |
| Access | Read-Write |
| Status | Current |
| Value list | 1 : 1..65535 |
| Parent node | swL2IGMPCtrlEntry |
| First child | None |
| Description | The frequency at which IGMP Host-Query packets are transmitted on this switch. |

D-link Switch: DGS-3627 **Firmware:** R1 **MIB File:** V1

Show Layer2 IGMP Max Response Time

:: Command ::

```
snmpwalk -v2c -c public 192.168.0.1 1.3.6.1.4.1.171.11.70.6.2.11.3.1.3
```

| | |
|-----------------|---|
| Object name | swL2IGMPMaxResponseTime |
| Object ID | 1.3.6.1.4.1.171.11.70.6.2.11.3.1.3 |
| Module | DGS3627-L2MGMT-MIB |
| Base syntax | Integer |
| Composed syntax | INTEGER |
| Access | Read-Write |
| Status | Current |
| Value list | 1 : 1..25 |
| Parent node | swL2IGMPCtrlEntry |
| First child | None |
| Description | The maximum query response time on this switch. |

Show Layer2 IGMP Robustness

:: Command ::

```
snmpwalk -v2c -c public 192.168.0.1 1.3.6.1.4.1.171.11.70.6.2.11.3.1.4
```

| | |
|-----------------|---|
| Object name | swL2IGMPRobustness |
| Object ID | 1.3.6.1.4.1.171.11.70.6.2.11.3.1.4 |
| Module | DGS3627-L2MGMT-MIB |
| Base syntax | Integer |
| Composed syntax | INTEGER |
| Access | Read-Write |
| Status | Current |
| Value list | 1 : 1..255 |
| Parent node | swL2IGMPCtrlEntry |
| First child | None |
| Description | The Robustness Variable allows tuning for the expected packet loss on a subnet. If a subnet is expected to be lossy, the Robustness Variable may be increased. IGMP is robust to (Robustness Variable-1) packet losses. |

D-link Switch: DGS-3627 **Firmware:** R1 **MIB File:** V1

Show Layer2 IGMP Last Member Query Interval

:: Command ::

```
snmpwalk -v2c -c public 192.168.0.1 1.3.6.1.4.1.171.11.70.6.2.11.3.1.5
```

| | |
|-----------------|--|
| Object name | swL2IGMPLastMemberQueryInterval |
| Object ID | 1.3.6.1.4.1.171.11.70.6.2.11.3.1.5 |
| Module | DGS3627-L2MGMT-MIB |
| Base syntax | Integer |
| Composed syntax | INTEGER |
| Access | Read-Write |
| Status | Current |
| Value list | 1 : 1..25 |
| Parent node | swL2IGMPCtrlEntry |
| First child | None |
| Description | The Last Member Query Interval is the Max Response Time inserted into Group-Specific Queries sent in response to Leave Group messages, and is also the amount of time between Group-Specific Query messages. |

Show Layer2 IGMP Host Timeout

:: Command ::

```
snmpwalk -v2c -c public 192.168.0.1 1.3.6.1.4.1.171.11.70.6.2.11.3.1.6
```

| | |
|-----------------|--|
| Object name | swL2IGMPHostTimeout |
| Object ID | 1.3.6.1.4.1.171.11.70.6.2.11.3.1.6 |
| Module | DGS3627-L2MGMT-MIB |
| Base syntax | Integer |
| Composed syntax | INTEGER |
| Access | Read-Write |
| Status | Current |
| Value list | 1 : 1..16711450 |
| Parent node | swL2IGMPCtrlEntry |
| First child | None |
| Description | The timer value for sending IGMP query packet when none was sent by the host in the LAN. The timer works in per-VLAN basis. Our device will be activated to send the query message if the timer is expired. Please reference RFC2236-1997. |

D-link Switch: DGS-3627 **Firmware:** R1 **MIB File:** V1

Show Layer2 IGMP Route Timeout

:: Command ::

```
snmpwalk -v2c -c public 192.168.0.1 1.3.6.1.4.1.171.11.70.6.2.11.3.1.7
```

| | |
|-----------------|---|
| Object name | swL2IGMPRouteTimeout |
| Object ID | 1.3.6.1.4.1.171.11.70.6.2.11.3.1.7 |
| Module | DGS3627-L2MGMT-MIB |
| Base syntax | Integer |
| Composed syntax | INTEGER |
| Access | Read-Write |
| Status | Current |
| Value list | 1 : 1..16711450 |
| Parent node | swL2IGMPCtrlEntry |
| First child | None |
| Description | The Router Timeout is how long a host must wait after hearing a Query before it may send any IGMPv2 messages. |

Show Layer2 IGMP Leave Timer

:: Command ::

```
snmpwalk -v2c -c public 192.168.0.1 1.3.6.1.4.1.171.11.70.6.2.11.3.1.8
```

| | |
|-----------------|--|
| Object name | swL2IGMPLeaveTimer |
| Object ID | 1.3.6.1.4.1.171.11.70.6.2.11.3.1.8 |
| Module | DGS3627-L2MGMT-MIB |
| Base syntax | Integer |
| Composed syntax | INTEGER |
| Access | Read-Write |
| Status | Current |
| Value list | 1 : 1..16711450 |
| Parent node | swL2IGMPCtrlEntry |
| First child | None |
| Description | When a querier receives a Leave Group message for a group that has group members on the reception interface, it sends Group-Specific Queries every swL2IGMPLeaveTimer to the group being left. |

D-link Switch: DGS-3627 Firmware: R1 MIB File: V1

Show Layer2 IGMP Query State

:: Command ::

```
snmpwalk -v2c -c public 192.168.0.1 1.3.6.1.4.1.171.11.70.6.2.11.3.1.9
```

| | |
|-----------------|--|
| Object name | swL2IGMPQueryState |
| Object ID | 1.3.6.1.4.1.171.11.70.6.2.11.3.1.9 |
| Module | DGS3627-L2MGMT-MIB |
| Base syntax | Integer |
| Composed syntax | INTEGER |
| Access | Read-Write |
| Status | Current |
| Value list | 1 : other(1) 2 : disabled(2) 3 : enabled(3) |
| Parent node | swL2IGMPCtrlEntry |
| First child | None |
| Description | This object decide the IGMP query enabled or disabled. |

Show Layer2 IGMP Current State

:: Command ::

```
snmpwalk -v2c -c public 192.168.0.1 1.3.6.1.4.1.171.11.70.6.2.11.3.1.10
```

| | |
|-----------------|--|
| Object name | swL2IGMPCurrentState |
| Object ID | 1.3.6.1.4.1.171.11.70.6.2.11.3.1.10 |
| Module | DGS3627-L2MGMT-MIB |
| Base syntax | Integer |
| Composed syntax | INTEGER |
| Access | Read-Only |
| Status | Current |
| Value list | 1 : other(1) 2 : querier(2) 3 : non-querier(3) |
| Parent node | swL2IGMPCtrlEntry |
| First child | None |
| Description | This object indicates the current IGMP query state. |

D-link Switch: DGS-3627 Firmware: R1 MIB File: V1

Show Layer2 IGMP Control State

:: Command ::

```
snmpwalk -v2c -c public 192.168.0.1 1.3.6.1.4.1.171.11.70.6.2.11.3.1.11
```

| | |
|-----------------|--|
| Object name | swL2IGMPCtrlState |
| Object ID | 1.3.6.1.4.1.171.11.70.6.2.11.3.1.11 |
| Module | DGS3627-L2MGMT-MIB |
| Base syntax | Integer |
| Composed syntax | INTEGER |
| Access | Read-Write |
| Status | Current |
| Value list | 1 : other(1) 2 : disable(2) 3 : enable(3) |
| Parent node | swL2IGMPCtrlEntry |
| First child | None |
| Description | This object indicates the status of this entry. other(1) - this entry is currently in use but the conditions under which it will remain so are different from each of the following values. disable(2) - IGMP function is disabled for this entry. enable(3) - IGMP function is enabled for this entry. |

D-link Switch: DGS-3627 Firmware: R1 MIB File: V1

Show Layer2 IGMP Leave State

:: Command ::

```
snmpwalk -v2c -c public 192.168.0.1 1.3.6.1.4.1.171.11.64.1.2.10.3.1.12
```

| | |
|-----------------|---|
| Object name | swL2IGMPFastLeaveState |
| Object ID | 1.3.6.1.4.1.171.11.70.6.2.11.3.1.12 |
| Module | DGS3627-L2MGMT-MIB |
| Base syntax | Integer |
| Composed syntax | INTEGER |
| Access | Read-Write |
| Status | Current |
| Value list | 1 : other(1) 2 : disable(2) 3 : enable(3) |
| Parent node | swL2IGMPCtrlEntry |
| First child | None |
| Description | This object indicates the fast_leave status of this entry. other(1) - this entry is currently in use but the conditions under which it will remain so are different from each of the following values. disable(2) - IGMP fast-leave function is disabled for this entry. enable(3) - IGMP fast-leave function is enabled for this entry. |

IGMP Info Table

| | |
|-------------|--|
| Object name | swL2IGMPInfoTable |
| Object ID | 1.3.6.1.4.1.171.11.70.6.2.11.5 |
| Module | DGS3627-L2MGMT-MIB |
| Base syntax | Sequence Of swL2IGMPInfoEntry |
| Access | Not_Accessible |
| Status | Current |
| Sequence | 1:swL2IGMPVid - Integer 2:swL2IGMPGroupIpAddr - IP Address 3:swL2IGMPMacAddr - Octet String 4:swL2IGMPPortMap - Octet String 5:swL2IGMPIpGroupReportCount - Integer |
| Parent node | swL2IGMPMgmt |
| First child | swL2IGMPInfoEntry |
| Description | The table containing current IGMP information which captured by this device, provided that swL2DevCtrlIGMPSnooping and swL2IGMPCtrlState of associated VLAN entry are all enabled. Note that the priority of IGMP table entries is lower than Filtering Table, i.e. if there is a table hash collision between the entries of IGMP Table and Filtering Table inside the switch H/W address table, then Filtering Table entry overwrite the colliding entry of IGMP Table. See swL2FilterMgmt description also. |

Show Layer2 IGMP PVID

:: Command ::

```
snmpwalk -v2c -c public 192.168.0.1 1.3.6.1.4.1.171.11.70.6.2.11.5.1.1
```

| | |
|-----------------|--|
| Object name | swL2IGMPVid |
| Object ID | 1.3.6.1.4.1.171.11.70.6.2.11.5.1.1 |
| Module | DGS3627-L2MGMT-MIB |
| Base syntax | Integer |
| Composed syntax | INTEGER |
| Access | Read-Only |
| Status | Current |
| Value list | 1 : 0..65535 |
| Parent node | swL2IGMPInfoEntry |
| First child | None |
| Description | This object indicates the Vid of individual IGMP table entry. It shows the Vid of IGMP report information captured on network. |

D-link Switch: DGS-3627 **Firmware:** R1 **MIB File:** V1

Show Layer2 IGMP Group IP Address

:: Command ::

```
snmpwalk -v2c -c public 192.168.0.1 1.3.6.1.4.1.171.11.70.6.2.11.5.1.2
```

| | |
|-----------------|---|
| Object name | swL2IGMPGroupIpAddr |
| Object ID | 1.3.6.1.4.1.171.11.70.6.2.11.5.1.2 |
| Module | DGS3627-L2MGMT-MIB |
| Base syntax | IP Address |
| Composed syntax | IpAddress |
| Access | Read-Only |
| Status | Current |
| Parent node | swL2IGMPInfoEntry |
| First child | None |
| Description | This object is identify group ip address which is captured from IGMP packet, in per-Vlan basis. |

Show Layer2 IGMP Group Mac Address

:: Command ::

```
snmpwalk -v2c -c public 192.168.0.1 1.3.6.1.4.1.171.11.70.6.2.11.5.1.3
```

| | |
|-----------------|---|
| Object name | swL2IGMPMacAddr |
| Object ID | 1.3.6.1.4.1.171.11.70.6.2.11.5.1.3 |
| Module | DGS3627-L2MGMT-MIB |
| Base syntax | Octet String |
| Composed syntax | MacAddress |
| Access | Read-Only |
| Status | Current |
| Value list | 1 : 6..6 |
| Parent node | swL2IGMPInfoEntry |
| First child | None |
| Description | This object is identify mac address which is corresponding to swL2IGMPGroupIpAddr, in per-Vlan basis. |

D-link Switch: DGS-3627 Firmware: R1 MIB File: V1

Show Layer2 IGMP Port Map

:: Command ::

```
snmpwalk -v2c -c public 192.168.0.1 1.3.6.1.4.1.171.11.70.6.2.11.5.1.4
```

| | |
|-----------------|---|
| Object name | swL2IGMPPortMap |
| Object ID | 1.3.6.1.4.1.171.11.70.6.2.11.5.1.4 |
| Module | DGS3627-L2MGMT-MIB |
| Base syntax | Octet String |
| Composed syntax | PortList |
| Access | Read-Only |
| Status | Current |
| Value list | 1 : 0..127 |
| Parent node | swL2IGMPInfoEntry |
| First child | None |
| Description | This object indicates which ports are belong to the same multicast group, in per-Vlan basis. Each multicast group has a octet string to indicate with port map. The most significant bit represents the lowest numbered port, and the least significant bit represents the highest numbered port. Thus, each port of the switch is represented by a single bit within the value of this object. If that bit has a value of '1' then that port is included in the set of ports; the port is not included if its bit has a value of '0'(Note that the setting of the bit corresponding to the port from which a frame is received is irrelevant). The 4 octets is represent one unit port according its logic port. If the unit less 32 port, the other port don't care just fill zero. |

Show Layer2 IGMP IP Group Report Count

:: Command ::

```
snmpwalk -v2c -c public 192.168.0.1 1.3.6.1.4.1.171.11.70.1.2.11.5.1.5
```

| | |
|-----------------|--|
| Object name | swL2IGMPIpGroupReportCount |
| Object ID | 1.3.6.1.4.1.171.11.70.6.2.11.5.1.5 |
| Module | DGS3627-L2MGMT-MIB |
| Base syntax | Integer |
| Composed syntax | INTEGER |
| Access | Read-Only |
| Status | Current |
| Value list | 1 : 0..65535 |
| Parent node | swL2IGMPInfoEntry |
| First child | None |
| Description | This object indicate how much report packet was receive by our device corresponding with this entry from IGMP function enabled, in per-Vlan basis. |

Layer 2 IGMP Router Port Table

| | |
|-------------|---|
| Object name | swL2IGMPRouterPortsTable |
| Object ID | 1.3.6.1.4.1.171.11.70.6.2.11.6 |
| Module | DGS3627-L2MGMT-MIB |
| Base syntax | Sequence Of swL2IGMPRouterPortsEntry |
| Access | Not_Accessible |
| Status | Current |
| Sequence | 1:swL2IGMPRouterPortsVid - Integer 2:swL2IGMPRouterStaticPortList - Octet String 3:swL2IGMPRouterDynamicPortList - Octet String 4:swL2IGMPRouterForbiddenPortList - Octet String |
| Parent node | swL2IGMPMgmt |
| First child | swL2IGMPRouterPortsEntry |
| Description | The table controls the Vlan's IGMP router ports function. |

Show Layer2 IGMP Router Port VLAN ID

:: Command ::

```
snmpwalk -v2c -c public 192.168.0.1 1.3.6.1.4.1.171.11.70.6.2.11.6.1.1
```

| | |
|-----------------|---|
| Object name | swL2IGMPRouterPortsVid |
| Object ID | 1.3.6.1.4.1.171.11.70.6.2.11.6.1.1 |
| Module | DGS3627-L2MGMT-MIB |
| Base syntax | Integer |
| Composed syntax | INTEGER |
| Access | Read-Only |
| Status | Current |
| Value list | 1 : 0..65535 |
| Parent node | swL2IGMPRouterPortsEntry |
| First child | None |
| Description | This object indicates the IGMP router ports entry's VLAN id. If VLAN is disabled, the Vid is always 0 and cannot be changed by management users. If VLAN is in Port-Base mode, the Vid is arranged from 1 to 12, fixed form. If VLAN is in 802.1q mode, the Vid setting can vary from 1 to 4094 by management user, and the Vid in each entry must be unique in the IGMP ports Table. |

D-link Switch: DGS-3627 **Firmware:** R1 **MIB File:** V1

Show Layer2 IGMP Router Port Static PortList

:: Command ::

```
snmpwalk -v2c -c public 192.168.0.1 1.3.6.1.4.1.171.11.70.6.2.11.6.1.2
```

| | |
|-----------------|------------------------------------|
| Object name | swL2IGMPRouterStaticPortList |
| Object ID | 1.3.6.1.4.1.171.11.70.6.2.11.6.1.2 |
| Module | DGS3627-L2MGMT-MIB |
| Base syntax | Octet String |
| Composed syntax | PortList |
| Access | Read-Write |
| Status | Current |
| Value list | 1 : 0..127 |
| Parent node | swL2IGMPRouterPortsEntry |
| First child | None |
| Description | |

Show Layer2 IGMP Router Port Dynamic Port List

:: Command ::

```
snmpwalk -v2c -c public 192.168.0.1 1.3.6.1.4.1.171.11.70.6.2.11.6.1.3
```

| | |
|-----------------|------------------------------------|
| Object name | swL2IGMPRouterDynamicPortList |
| Object ID | 1.3.6.1.4.1.171.11.70.6.2.11.6.1.3 |
| Module | DGS3627-L2MGMT-MIB |
| Base syntax | Octet String |
| Composed syntax | PortList |
| Access | Read-Only |
| Status | Current |
| Value list | 1 : 0..127 |
| Parent node | swL2IGMPRouterPortsEntry |
| First child | None |
| Description | |

D-link Switch: DGS-3627 **Firmware:** R1 **MIB File:** V1

Show Layer2 IGMP Router Forbidden Port List

:: Command ::

```
snmpwalk -v2c -c public 192.168.0.1 1.3.6.1.4.1.171.11.70.6.2.11.6.1.4
```

| | |
|-----------------|------------------------------------|
| Object name | swL2IGMPRouterForbiddenPortList |
| Object ID | 1.3.6.1.4.1.171.11.70.6.2.11.6.1.4 |
| Module | DGS3627-L2MGMT-MIB |
| Base syntax | Octet String |
| Composed syntax | PortList |
| Access | Read-Write |
| Status | Current |
| Value list | 1 : 0..127 |
| Parent node | swL2IGMPRouterPortsEntry |
| First child | None |
| Description | |

D-link Switch: DGS-3627 Firmware: R1 MIB File: V1

Enable IGMP Snooping

Step 1. Set up Query State to be “Enable”

```
snmpset -v2c -c private 192.168.0.1 1.3.6.1.4.1.171.11.70.6.2.11.3.1.9.1 i 3
```

Step 2. Enable Control State to be “Enable”

```
snmpset -v2c -c private 192.168.0.1 1.3.6.1.4.1.171.11.70.6.2.11.3.1.11.1 i 3
```

Step 3. Enable Global IGMP Snooping Function

```
snmpset -v2c -c private 192.168.0.1 1.3.6.1.4.1.171.11.70.6.2.1.2.2.0 i 3
```

| | |
|-----------------|--|
| Object name | swL2DevCtrlIGMPSnooping |
| Object ID | 1.3.6.1.4.1.171.11.70.6.2.1.2.2 |
| Module | DGS3627-L2MGMT-MIB |
| Base syntax | Integer |
| Composed syntax | INTEGER |
| Access | Read-Write |
| Status | Current |
| Value list | 1 : other(1) 2 : disabled(2) 3 : enabled(3) |
| Parent node | swL2DevCtrl |
| First child | None |
| Description | This object indicates layer 2 Internet Group Management Protocol (IGMP) capture function is enabled or disabled. |

Step 4. IGMP Snooping multicast filter

```
snmpset -v2c -c private 192.168.0.1 1.3.6.1.4.1.171.11.70.6.2.2.1.1.2.1 i 3
```

3 → forward-unregistered-groups

| | |
|-----------------|--|
| Object name | swL2MultiFilterMode |
| Object ID | 1.3.6.1.4.1.171.11.70.6.2.2.1.1.2 |
| Module | DGS3627-L2MGMT-MIB |
| Base syntax | Integer |
| Composed syntax | INTEGER |
| Access | Read-Write |
| Status | Current |
| Value list | 1 : forward-all-groups(1) 2 : forward-unregistered-groups(2) 3 : filter-unregistered-groups(3) |
| Parent node | swL2MultiFilterEntry |
| First child | None |
| Description | vlan multicast filter mode. |