

How to Configure Limited Multicast Addresses via SNMP

The related OID located in **swL2MgmtMIB**

Following is the related OID for DES-3028/52 series

1.3.6.1.4.1.171.11.63.6.2	DES-3028
1.3.6.1.4.1.171.11.63.7.2	DES-3028P
1.3.6.1.4.1.171.11.63.8.2	DES-3052
1.3.6.1.4.1.171.11.63.9.2	DES-3052P
1.3.6.1.4.1.171.11.63.11.2	DES-3028G

Take DES-3028 for example

In DES-3028 , Set multicast filter on port 1,2,3

Command

```
snmpset -v2c -c private 10.90.90.91 1.3.6.1.4.1.171.11.63.6.2.22.2.1.2.1 s abc  
1.3.6.1.4.1.171.11.63.6.2.22.2.1.3.1 i 2 1.3.6.1.4.1.171.11.63.6.2.22.2.1.4.1 s 224.1.1.5-224.1.1.6  
1.3.6.1.4.1.171.11.63.6.2.22.2.1.5.1 i 4
```

Create Multicast Filter Profile Name “abc”

```
snmpset -v2c -c private 10.90.90.91 1.3.6.1.4.1.171.11.63.6.2.22.2.1.2.1 s abc
```

Add Multicast Filter Group List “224.1.1.5 ~ 224.1.1.6”

```
snmpset -v2c -c private 10.90.90.91 1.3.6.1.4.1.171.11.63.6.2.22.2.1.4.1 s 224.1.1.5-224.1.1.6
```

Add One More Group List “224.1.1.8-224.1.1.9”

```
snmpset -v2c -c private 10.90.90.90 1.3.6.1.4.1.171.11.63.6.2.22.2.1.3.1 i 2  
1.3.6.1.4.1.171.11.63.6.2.22.2.1.4.1 s 224.1.1.8-224.1.1.9
```

Assign multicast filter profile on port 1

```
snmpset -v2c -c private 10.90.90.91 1.3.6.1.4.1.171.11.63.6.2.22.3.1.2.1 i 2  
1.3.6.1.4.1.171.11.63.6.2.22.3.1.3.1 i 1
```

Assign multicast filter profile on port 2

```
snmpset -v2c -c private 10.90.90.91 1.3.6.1.4.1.171.11.63.6.2.22.3.1.2.2 i 2  
1.3.6.1.4.1.171.11.63.6.2.22.3.1.3.2 i 1
```

Assign multicast filter profile on port 3

```
snmpset -v2c -c private 10.90.90.91 1.3.6.1.4.1.171.11.63.6.2.22.3.1.2.3 i 2  
1.3.6.1.4.1.171.11.63.6.2.22.3.1.3.3 i 1
```

Related OID

swL2MultiFilter	Object name	swL2MultiFilter
swL2McastFilterTable	Object ID	1.3.6.1.4.1.171.11.63.6.2.22
swL2McastFilterEntry	Module	DES3028-L2MGMT-MIB
swL2McastFilterProfileIndex	Base syntax	Object Identifier
swL2McastFilterProfileName	Access	Not_Accessible
swL2McastFilterAddOrDelState	Status	Mandatory
swL2McastFilterGroupList	Parent node	swL2MgmtMIB
swL2McastFilterStatus	First child	swL2McastFilterTable
swL2McastFilterPortTable		
swL2McastFilterPortEntry		
swL2McastFilterPortGroupPortIndex		
swL2McastFilterPortProfileAddOrDelState		
swL2McastFilterPortProfileID		
swL2McastFilterPortMaxGroupTable		
swL2McastFilterPortMaxGroupEntry		
swL2McastFilterPortMaxGroupPortIndex		
swL2McastFilterPortMaxGroup		
swL2McastFilterPortInfoTable		
swL2McastFilterPortInfoEntry		
swL2McastFilterPortInfoPortIndex		
swL2McastFilterPortInfoProfileName		

swL2MultiFilter	Object name	swL2McastFilterTable
swL2McastFilterTable	Object ID	1.3.6.1.4.1.171.11.63.6.2.22.2
swL2McastFilterEntry	Module	DES3028-L2MGMT-MIB
swL2McastFilterProfileIndex	Base syntax	Sequence Of swL2McastFilterEntry
swL2McastFilterProfileName	Access	Not_Accessible
swL2McastFilterAddOrDelState	Status	Current
swL2McastFilterGroupList	Sequence	1:swL2McastFilterProfileIndex - Integer 2:swL2McastFilterProfileName - Octet String 3:swL2McastFilterAddOrDelState - Integer 4:swL2McastFilterGroupList - Octet String 5:swL2McastFilterStatus - Integer
swL2McastFilterStatus	Parent node	swL2MultiFilter
swL2McastFilterPortTable	First child	swL2McastFilterEntry
swL2McastFilterPortEntry	Description	A table that contains information about the multicast filter address.
swL2McastFilterPortGroupPortIndex		
swL2McastFilterPortProfileAddOrDelState		
swL2McastFilterPortProfileID		
swL2McastFilterPortMaxGroupTable		
swL2McastFilterPortMaxGroupEntry		
swL2McastFilterPortMaxGroupPortIndex		
swL2McastFilterPortMaxGroup		
swL2McastFilterPortInfoTable		
swL2McastFilterPortInfoEntry		
swL2McastFilterPortInfoPortIndex		
swL2McastFilterPortInfoProfileName		

	<table border="1"> <tr><td>Object name</td><td>swL2McastFilterEntry</td></tr> <tr><td>Object ID</td><td>1.3.6.1.4.1.171.11.63.6.2.22.2.1</td></tr> <tr><td>Module</td><td>DES3028-L2MGMT-MIB</td></tr> <tr><td>Base syntax</td><td>Sequence</td></tr> <tr><td>Access</td><td>Not_Accessible</td></tr> <tr><td>Status</td><td>Current</td></tr> <tr><td>Index</td><td>1.swL2McastFilterProfileIndex</td></tr> <tr><td>Parent node</td><td>swL2McastFilterTable</td></tr> <tr><td>First child</td><td>swL2McastFilterProfileIndex</td></tr> <tr><td>Description</td><td>A list of multicast filter mode information for each profile ID.</td></tr> </table>	Object name	swL2McastFilterEntry	Object ID	1.3.6.1.4.1.171.11.63.6.2.22.2.1	Module	DES3028-L2MGMT-MIB	Base syntax	Sequence	Access	Not_Accessible	Status	Current	Index	1.swL2McastFilterProfileIndex	Parent node	swL2McastFilterTable	First child	swL2McastFilterProfileIndex	Description	A list of multicast filter mode information for each profile ID.
Object name	swL2McastFilterEntry																				
Object ID	1.3.6.1.4.1.171.11.63.6.2.22.2.1																				
Module	DES3028-L2MGMT-MIB																				
Base syntax	Sequence																				
Access	Not_Accessible																				
Status	Current																				
Index	1.swL2McastFilterProfileIndex																				
Parent node	swL2McastFilterTable																				
First child	swL2McastFilterProfileIndex																				
Description	A list of multicast filter mode information for each profile ID.																				

	<table border="1"> <tr><td>Object name</td><td>swL2McastFilterProfileIndex</td></tr> <tr><td>Object ID</td><td>1.3.6.1.4.1.171.11.63.6.2.22.2.1.1</td></tr> <tr><td>Module</td><td>DES3028-L2MGMT-MIB</td></tr> <tr><td>Base syntax</td><td>Integer</td></tr> <tr><td>Composed syntax</td><td>INTEGER</td></tr> <tr><td>Access</td><td>Read-Only</td></tr> <tr><td>Status</td><td>Current</td></tr> <tr><td>Value list</td><td>1 : 1..24</td></tr> <tr><td>Parent node</td><td>swL2McastFilterEntry</td></tr> <tr><td>First child</td><td>None</td></tr> <tr><td>Description</td><td>index for each profile</td></tr> </table>	Object name	swL2McastFilterProfileIndex	Object ID	1.3.6.1.4.1.171.11.63.6.2.22.2.1.1	Module	DES3028-L2MGMT-MIB	Base syntax	Integer	Composed syntax	INTEGER	Access	Read-Only	Status	Current	Value list	1 : 1..24	Parent node	swL2McastFilterEntry	First child	None	Description	index for each profile
Object name	swL2McastFilterProfileIndex																						
Object ID	1.3.6.1.4.1.171.11.63.6.2.22.2.1.1																						
Module	DES3028-L2MGMT-MIB																						
Base syntax	Integer																						
Composed syntax	INTEGER																						
Access	Read-Only																						
Status	Current																						
Value list	1 : 1..24																						
Parent node	swL2McastFilterEntry																						
First child	None																						
Description	index for each profile																						

	<table border="1"> <tr><td>Object name</td><td>swL2McastFilterProfileName</td></tr> <tr><td>Object ID</td><td>1.3.6.1.4.1.171.11.63.6.2.22.2.1.2</td></tr> <tr><td>Module</td><td>DES3028-L2MGMT-MIB</td></tr> <tr><td>Base syntax</td><td>Octet String</td></tr> <tr><td>Composed syntax</td><td>DisplayString</td></tr> <tr><td>Access</td><td>Read-Write</td></tr> <tr><td>Status</td><td>Current</td></tr> <tr><td>Value list</td><td>1 : 1..32</td></tr> <tr><td>Parent node</td><td>swL2McastFilterEntry</td></tr> <tr><td>First child</td><td>None</td></tr> <tr><td>Description</td><td>The multicast filter description.</td></tr> </table>	Object name	swL2McastFilterProfileName	Object ID	1.3.6.1.4.1.171.11.63.6.2.22.2.1.2	Module	DES3028-L2MGMT-MIB	Base syntax	Octet String	Composed syntax	DisplayString	Access	Read-Write	Status	Current	Value list	1 : 1..32	Parent node	swL2McastFilterEntry	First child	None	Description	The multicast filter description.
Object name	swL2McastFilterProfileName																						
Object ID	1.3.6.1.4.1.171.11.63.6.2.22.2.1.2																						
Module	DES3028-L2MGMT-MIB																						
Base syntax	Octet String																						
Composed syntax	DisplayString																						
Access	Read-Write																						
Status	Current																						
Value list	1 : 1..32																						
Parent node	swL2McastFilterEntry																						
First child	None																						
Description	The multicast filter description.																						

	<table border="1"> <tr><td>Object name</td><td>swL2McastFilterAddOrDelState</td></tr> <tr><td>Object ID</td><td>1.3.6.1.4.1.171.11.63.6.2.22.2.1.3</td></tr> <tr><td>Module</td><td>DES3028-L2MGMT-MIB</td></tr> <tr><td>Base syntax</td><td>Integer</td></tr> <tr><td>Composed syntax</td><td>INTEGER</td></tr> <tr><td>Access</td><td>Read-Write</td></tr> <tr><td>Status</td><td>Current</td></tr> <tr><td>Value list</td><td>1 : none(1) 2 : add(2) 3 : delete(3)</td></tr> <tr><td>Parent node</td><td>swL2McastFilterEntry</td></tr> <tr><td>First child</td><td>None</td></tr> <tr><td>Description</td><td>The control multicast filter address.</td></tr> </table>	Object name	swL2McastFilterAddOrDelState	Object ID	1.3.6.1.4.1.171.11.63.6.2.22.2.1.3	Module	DES3028-L2MGMT-MIB	Base syntax	Integer	Composed syntax	INTEGER	Access	Read-Write	Status	Current	Value list	1 : none(1) 2 : add(2) 3 : delete(3)	Parent node	swL2McastFilterEntry	First child	None	Description	The control multicast filter address.
Object name	swL2McastFilterAddOrDelState																						
Object ID	1.3.6.1.4.1.171.11.63.6.2.22.2.1.3																						
Module	DES3028-L2MGMT-MIB																						
Base syntax	Integer																						
Composed syntax	INTEGER																						
Access	Read-Write																						
Status	Current																						
Value list	1 : none(1) 2 : add(2) 3 : delete(3)																						
Parent node	swL2McastFilterEntry																						
First child	None																						
Description	The control multicast filter address.																						

	<p>Object name swL2McastFilterGroupList Object ID 1.3.6.1.4.1.171.11.63.6.2.22.2.1.4 Module DES3028-L2MGMT-MIB</p> <p>Base syntax Octet String Composed syntax DisplayString Access Read-Write Status Current</p> <p>Parent node swL2McastFilterEntry First child None Description The multicast filter address group list.</p>
--	--

	<p>Object name swL2McastFilterStatus Object ID 1.3.6.1.4.1.171.11.63.6.2.22.2.1.5 Module DES3028-L2MGMT-MIB</p> <p>Base syntax Integer Composed syntax RowStatus Access Read-CREATE Status Current</p> <p>Value list</p> <table border="1"> <tr><td>1 : active(1)</td></tr> <tr><td>2 : notInService(2)</td></tr> <tr><td>3 : notReady(3)</td></tr> <tr><td>4 : createAndGo(4)</td></tr> <tr><td>5 : createAndWait(5)</td></tr> <tr><td>6 : destroy(6)</td></tr> </table> <p>Parent node swL2McastFilterEntry First child None Description This object indicates the status of this entry.</p>	1 : active(1)	2 : notInService(2)	3 : notReady(3)	4 : createAndGo(4)	5 : createAndWait(5)	6 : destroy(6)
1 : active(1)							
2 : notInService(2)							
3 : notReady(3)							
4 : createAndGo(4)							
5 : createAndWait(5)							
6 : destroy(6)							

	<p>Object name swL2McastFilterPortTable Object ID 1.3.6.1.4.1.171.11.63.6.2.22.3 Module DES3028-L2MGMT-MIB</p> <p>Base syntax Sequence Of swL2McastFilterPortEntry Access Not_Accessible Status Current</p> <p>Sequence</p> <ul style="list-style-type: none"> 1:swL2McastFilterPortGroupPortIndex - Integer 2:swL2McastFilterPortProfileAddOrDelState - Integer 3:swL2McastFilterPortProfileID - Integer <p>Parent node swL2MultiFilter First child swL2McastFilterPortEntry Description A table that is used to bind port to profile ID.</p>
--	---

	<p>Object name swL2McastFilterPortEntry Object ID 1.3.6.1.4.1.171.11.63.6.2.22.3.1 Module DES3028-L2MGMT-MIB</p> <p>Base syntax Sequence Access Not_Accessible Status Current</p> <p>Index 1.swL2McastFilterPortGroupPortIndex</p> <p>Parent node swL2McastFilterPortTable First child swL2McastFilterPortGroupPortIndex Description A list of information that is used to bind port to profile ID.</p>
--	---

<pre> swL2MultiFilter ├── swL2McastFilterTable │ ├── swL2McastFilterEntry │ │ ├── swL2McastFilterProfileIndex │ │ ├── swL2McastFilterProfileName │ │ ├── swL2McastFilterAddOrDeleteState │ │ ├── swL2McastFilterGroupList │ │ └── swL2McastFilterStatus │ └── swL2McastFilterPortTable │ ├── swL2McastFilterPortEntry │ │ ├── swL2McastFilterPortProfileIndex │ │ ├── swL2McastFilterPortProfileAddOrDeleteState │ │ ├── swL2McastFilterPortProfileID │ │ └── swL2McastFilterPortMaxGroupTable │ │ ├── swL2McastFilterPortMaxGroupEntry │ │ │ ├── swL2McastFilterPortMaxGroupIndex │ │ │ ├── swL2McastFilterPortMaxGroupPortIndex │ │ │ └── swL2McastFilterPortMaxGroup │ └── swL2McastFilterPortInfoTable │ ├── swL2McastFilterPortInfoEntry │ │ ├── swL2McastFilterPortInfoPortIndex │ │ ├── swL2McastFilterPortInfoProfileName </pre>	<table border="0"> <tr> <td>Object name</td><td>swL2McastFilterPortGroupPortIndex</td></tr> <tr> <td>Object ID</td><td>1.3.6.1.4.1.171.11.63.6.2.22.3.1.1</td></tr> <tr> <td>Module</td><td>DES3028-L2MGMT-MIB</td></tr> <tr> <td> </td><td> </td></tr> <tr> <td>Base syntax</td><td>Integer</td></tr> <tr> <td>Composed syntax</td><td>INTEGER</td></tr> <tr> <td>Access</td><td>Read-Only</td></tr> <tr> <td>Status</td><td>Current</td></tr> <tr> <td> </td><td> </td></tr> <tr> <td>Parent node</td><td>swL2McastFilterPortEntry</td></tr> <tr> <td>First child</td><td>None</td></tr> <tr> <td>Description</td><td>The port index.</td></tr> </table>	Object name	swL2McastFilterPortGroupPortIndex	Object ID	1.3.6.1.4.1.171.11.63.6.2.22.3.1.1	Module	DES3028-L2MGMT-MIB			Base syntax	Integer	Composed syntax	INTEGER	Access	Read-Only	Status	Current			Parent node	swL2McastFilterPortEntry	First child	None	Description	The port index.
Object name	swL2McastFilterPortGroupPortIndex																								
Object ID	1.3.6.1.4.1.171.11.63.6.2.22.3.1.1																								
Module	DES3028-L2MGMT-MIB																								
Base syntax	Integer																								
Composed syntax	INTEGER																								
Access	Read-Only																								
Status	Current																								
Parent node	swL2McastFilterPortEntry																								
First child	None																								
Description	The port index.																								

swL2MultiFilter	Object name	swL2McastFilterPortProfileID
swL2McastFilterTable	Object ID	1.3.6.1.4.1.171.11.63.6.2.22.3.1.3
swL2McastFilterEntry	Module	DES3028-L2MGMT-MIB
swL2McastProfileIndex	Base syntax	Integer
swL2McastProfileName	Composed syntax	INTEGER
swL2McastFilterAddOrDeleteState	Access	Read-Write
swL2McastFilterGroupList	Status	Current
swL2McastFilterStatus	Value list	1 .. 0..24
swL2McastPortTable	Parent node	swL2McastFilterPortEntry
swL2McastFilterPortEntry	First child	None
swL2McastFilterPortGroupPortIndex	Description	This object indicates the profile ID of this entry. When read, it is always 0. When set, 0 can not be set.
swL2McastFilterPortProfileAddOrDeleteState		
swL2McastFilterPortProfileID		
swL2McastFilterPortMaxGroupTable		
swL2McastFilterPortMaxGroupEntry		
swL2McastFilterPortMaxGroupIndex		
swL2McastFilterPortMaxGroupPortIndex		
swL2McastFilterPortMaxGroup		
swL2McastFilterPortInfoTable		
swL2McastFilterPortInfoEntry		
swL2McastFilterPortInfoPortIndex		
swL2McastFilterPortInfoProfileName		

swL2MultiFilter	Object name	swL2McastFilterPortMaxGroupTable
	Object ID	1.3.6.1.4.1.171.11.63.6.2.22.4
	Module	DE53028-L2MGMT-MIB
	Base syntax	Sequence Of swL2McastFilterPortMaxGroupEntry
	Access	Not_Accessible
	Status	Current
	Sequence	1:swL2McastFilterPortMaxGroupPortIndex - Integer 2:swL2McastFilterPortMaxGroup - Integer
	Parent node	swL2MultiFilter
	First child	swL2McastFilterPortMaxGroupEntry
	Description	A table that contains information about the max group number based on port.

swL2MultiFilter	Object name	swL2McastFilterPortMaxGroupEntry
swL2McastFilterTable	Object ID	1.3.6.1.4.1.171.11.63.6.2.22.4.1
swL2McastFilterEntry	Module	DES3028-L2MGMT-MIB
swL2McastFilterProfileIndex	Base syntax	Sequence
swL2McastFilterProfileName	Access	Not_Accessible
swL2McastFilterAddOrDeleteState	Status	Current
swL2McastFilterGroupList	Index	1..swL2McastFilterPortMaxGroupPortIndex
swL2McastFilterStatus		
swL2McastFilterPortTable	Parent node	swL2McastFilterPortMaxGroupTable
swL2McastFilterPortEntry	First child	swL2McastFilterPortMaxGroupPortIndex
swL2McastFilterPortProfileIndex	Description	A list of max group number information for each port.
swL2McastFilterPortProfileAddOrDeleteState		
swL2McastFilterPortProfileID		
swL2McastFilterPortMaxGroupTable		
swL2McastFilterPortMaxGroupEntry		
swL2McastFilterPortMaxGroupIndex		
swL2McastFilterPortMaxGroupPortIndex		
swL2McastFilterPortMaxGroup		
swL2McastFilterPortInfoTable		
swL2McastFilterPortInfoEntry		
swL2McastFilterPortInfoPortIndex		
swL2McastFilterPortInfoProfileName		

swL2MultiFilter	Object name	swL2McastFilterPortMaxGroupPortIndex
swL2McastFilterTable	Object ID	1.3.6.1.4.1.171.11.63.6.2.22.4.1.1
swL2McastFilterEntry	Module	DE53028-L2MGMT-MIB
swL2McastFilterProfileIndex	Base syntax	Integer
swL2McastFilterProfileName	Composed syntax	INTEGER
swL2McastFilterAddOrDeleteState	Access	Read-Only
swL2McastFilterGroupList	Status	Current
swL2McastFilterStatus	Parent node	swL2McastFilterPortMaxGroupEntry
swL2McastFilterPortTable	First child	None
swL2McastFilterPortEntry	Description	The port index.
swL2McastFilterPortGroupIndex		
swL2McastFilterPortProfileAddOrDeleteState		
swL2McastFilterPortProfileID		
swL2McastFilterPortMaxGroupTable		
swL2McastFilterPortMaxGroupEntry		
swL2McastFilterPortMaxGroupPortIndex		
swL2McastFilterPortMaxGroupPortIndex		
swL2McastFilterPortMaxGroup		
swL2McastFilterPortInfoTable		
swL2McastFilterPortInfoEntry		
swL2McastFilterPortInfoPortIndex		
swL2McastFilterPortInfoProfileName		

swL2MultiFilter	Object name	swL2McastFilterPortMaxGroup
	Object ID	1.3.6.1.4.1.171.11.63.6.2.22.4.1.2
	Module	DES3028-L2MGMT-MIB
	Base syntax	Integer
	Composed syntax	INTEGER
	Access	Read-Write
	Status	Current
	Value list	1 : 1..256
	Parent node	swL2McastFilterPortMaxGroupEntry
	First child	None
Description		
The max group numbers. The default is 256.		

swL2MultiFilter	Object name	swL2McastFilterPortInfoTable
 swL2McastFilterTable	Object ID	1.3.6.1.4.1.171.11.63.6.2.22.5
 swL2McastFilterEntry	Module	DES3028-L2MGMT-MIB
swL2McastFilterProfileIndex	Base syntax	Sequence Of swL2McastFilterPortInfoEntry
swL2McastFilterProfileName	Access	Not_Accessible
swL2McastFilterAddOrDeleteState	Status	Current
swL2McastFilterGroupList	Sequence	1:swL2McastFilterPortInfoPortIndex - Integer 2:swL2McastFilterPortInfoProfileName - Octet String
swL2McastFilterStatus		
 swL2McastFilterPortTable		
 swL2McastFilterPortEntry	Parent node	swL2MultiFilter
swL2McastFilterPortGroupPortIndex	First child	swL2McastFilterPortInfoEntry
swL2McastFilterPortProfileAddOrDeleteState		
swL2McastFilterPortProfileID	Description	A table that contains information about all of the multicast groups for the ports.
 swL2McastFilterPortMaxGroupTable		
 swL2McastFilterPortMaxGroupEntry		
swL2McastFilterPortMaxGroupPortIndex		
swL2McastFilterPortMaxGroup		
 swL2McastFilterPortInfoTable		
 swL2McastFilterPortInfoEntry		
swL2McastFilterPortInfoPortIndex		
swL2McastFilterPortInfoProfileName		

<table border="1"> <tr><td>swL2MultiFilter</td><td></td></tr> <tr><td> swL2McastFilterTable</td><td></td></tr> <tr><td> swL2McastFilterEntry</td><td></td></tr> <tr><td> swL2McastFilterProfileIndex</td><td></td></tr> <tr><td> swL2McastFilterProfileName</td><td></td></tr> <tr><td> swL2McastFilterAddOrDelState</td><td></td></tr> <tr><td> swL2McastFilterGroupList</td><td></td></tr> <tr><td> swL2McastFilterStatus</td><td></td></tr> <tr><td> swL2McastFilterPortTable</td><td></td></tr> <tr><td> swL2McastFilterPortEntry</td><td></td></tr> <tr><td> swL2McastFilterPortGroupPortIndex</td><td></td></tr> <tr><td> swL2McastFilterPortProfileAddOrDelState</td><td></td></tr> <tr><td> swL2McastFilterPortProfileID</td><td></td></tr> <tr><td> swL2McastFilterPortMaxGroupTable</td><td></td></tr> <tr><td> swL2McastFilterPortMaxGroupEntry</td><td></td></tr> <tr><td> swL2McastFilterPortMaxGroupPortIndex</td><td></td></tr> <tr><td> swL2McastFilterPortMaxGroup</td><td></td></tr> <tr><td> swL2McastFilterPortInfoTable</td><td></td></tr> <tr><td> swL2McastFilterPortInfoEntry</td><td></td></tr> <tr><td> swL2McastFilterPortInfoPortIndex</td><td></td></tr> <tr><td> swL2McastFilterPortInfoProfileName</td><td></td></tr> </table>	swL2MultiFilter		swL2McastFilterTable		swL2McastFilterEntry		swL2McastFilterProfileIndex		swL2McastFilterProfileName		swL2McastFilterAddOrDelState		swL2McastFilterGroupList		swL2McastFilterStatus		swL2McastFilterPortTable		swL2McastFilterPortEntry		swL2McastFilterPortGroupPortIndex		swL2McastFilterPortProfileAddOrDelState		swL2McastFilterPortProfileID		swL2McastFilterPortMaxGroupTable		swL2McastFilterPortMaxGroupEntry		swL2McastFilterPortMaxGroupPortIndex		swL2McastFilterPortMaxGroup		swL2McastFilterPortInfoTable		swL2McastFilterPortInfoEntry		swL2McastFilterPortInfoPortIndex		swL2McastFilterPortInfoProfileName		<p>Object name: swL2McastFilterPortInfoEntry Object ID: 1.3.6.1.4.1.171.11.63.6.2.22.5.1 Module: DES3028-L2MGMT-MIB</p> <p>Base syntax: Sequence Access: Not_Accessible Status: Current Index: 1.swL2McastFilterPortInfoPortIndex</p> <p>Parent node: swL2McastFilterPortInfoTable First child: swL2McastFilterPortInfoPortIndex Description: A list of information about all of the multicast groups for each port.</p>
swL2MultiFilter																																											
swL2McastFilterTable																																											
swL2McastFilterEntry																																											
swL2McastFilterProfileIndex																																											
swL2McastFilterProfileName																																											
swL2McastFilterAddOrDelState																																											
swL2McastFilterGroupList																																											
swL2McastFilterStatus																																											
swL2McastFilterPortTable																																											
swL2McastFilterPortEntry																																											
swL2McastFilterPortGroupPortIndex																																											
swL2McastFilterPortProfileAddOrDelState																																											
swL2McastFilterPortProfileID																																											
swL2McastFilterPortMaxGroupTable																																											
swL2McastFilterPortMaxGroupEntry																																											
swL2McastFilterPortMaxGroupPortIndex																																											
swL2McastFilterPortMaxGroup																																											
swL2McastFilterPortInfoTable																																											
swL2McastFilterPortInfoEntry																																											
swL2McastFilterPortInfoPortIndex																																											
swL2McastFilterPortInfoProfileName																																											

<table border="1"> <tr><td>swL2MultiFilter</td><td></td></tr> <tr><td> swL2McastFilterTable</td><td></td></tr> <tr><td> swL2McastFilterEntry</td><td></td></tr> <tr><td> swL2McastFilterProfileIndex</td><td></td></tr> <tr><td> swL2McastFilterProfileName</td><td></td></tr> <tr><td> swL2McastFilterAddOrDelState</td><td></td></tr> <tr><td> swL2McastFilterGroupList</td><td></td></tr> <tr><td> swL2McastFilterStatus</td><td></td></tr> <tr><td> swL2McastFilterPortTable</td><td></td></tr> <tr><td> swL2McastFilterPortEntry</td><td></td></tr> <tr><td> swL2McastFilterPortGroupPortIndex</td><td></td></tr> <tr><td> swL2McastFilterPortProfileAddOrDelState</td><td></td></tr> <tr><td> swL2McastFilterPortProfileID</td><td></td></tr> <tr><td> swL2McastFilterPortMaxGroupTable</td><td></td></tr> <tr><td> swL2McastFilterPortMaxGroupEntry</td><td></td></tr> <tr><td> swL2McastFilterPortMaxGroupPortIndex</td><td></td></tr> <tr><td> swL2McastFilterPortMaxGroup</td><td></td></tr> <tr><td> swL2McastFilterPortInfoTable</td><td></td></tr> <tr><td> swL2McastFilterPortInfoEntry</td><td></td></tr> <tr><td> swL2McastFilterPortInfoPortIndex</td><td></td></tr> <tr><td> swL2McastFilterPortInfoProfileName</td><td></td></tr> </table>	swL2MultiFilter		swL2McastFilterTable		swL2McastFilterEntry		swL2McastFilterProfileIndex		swL2McastFilterProfileName		swL2McastFilterAddOrDelState		swL2McastFilterGroupList		swL2McastFilterStatus		swL2McastFilterPortTable		swL2McastFilterPortEntry		swL2McastFilterPortGroupPortIndex		swL2McastFilterPortProfileAddOrDelState		swL2McastFilterPortProfileID		swL2McastFilterPortMaxGroupTable		swL2McastFilterPortMaxGroupEntry		swL2McastFilterPortMaxGroupPortIndex		swL2McastFilterPortMaxGroup		swL2McastFilterPortInfoTable		swL2McastFilterPortInfoEntry		swL2McastFilterPortInfoPortIndex		swL2McastFilterPortInfoProfileName		<p>Object name: swL2McastFilterPortInfoPortIndex Object ID: 1.3.6.1.4.1.171.11.63.6.2.22.5.1.1 Module: DES3028-L2MGMT-MIB</p> <p>Base syntax: Integer Composed syntax: INTEGER Access: Read-Only Status: Current</p> <p>Parent node: swL2McastFilterPortInfoEntry First child: None Description: The port index.</p>
swL2MultiFilter																																											
swL2McastFilterTable																																											
swL2McastFilterEntry																																											
swL2McastFilterProfileIndex																																											
swL2McastFilterProfileName																																											
swL2McastFilterAddOrDelState																																											
swL2McastFilterGroupList																																											
swL2McastFilterStatus																																											
swL2McastFilterPortTable																																											
swL2McastFilterPortEntry																																											
swL2McastFilterPortGroupPortIndex																																											
swL2McastFilterPortProfileAddOrDelState																																											
swL2McastFilterPortProfileID																																											
swL2McastFilterPortMaxGroupTable																																											
swL2McastFilterPortMaxGroupEntry																																											
swL2McastFilterPortMaxGroupPortIndex																																											
swL2McastFilterPortMaxGroup																																											
swL2McastFilterPortInfoTable																																											
swL2McastFilterPortInfoEntry																																											
swL2McastFilterPortInfoPortIndex																																											
swL2McastFilterPortInfoProfileName																																											

<table border="1"> <tr><td>swL2MultiFilter</td><td></td></tr> <tr><td> swL2McastFilterTable</td><td></td></tr> <tr><td> swL2McastFilterEntry</td><td></td></tr> <tr><td> swL2McastFilterProfileIndex</td><td></td></tr> <tr><td> swL2McastFilterProfileName</td><td></td></tr> <tr><td> swL2McastFilterAddOrDelState</td><td></td></tr> <tr><td> swL2McastFilterGroupList</td><td></td></tr> <tr><td> swL2McastFilterStatus</td><td></td></tr> <tr><td> swL2McastFilterPortTable</td><td></td></tr> <tr><td> swL2McastFilterPortEntry</td><td></td></tr> <tr><td> swL2McastFilterPortGroupPortIndex</td><td></td></tr> <tr><td> swL2McastFilterPortProfileAddOrDelState</td><td></td></tr> <tr><td> swL2McastFilterPortProfileID</td><td></td></tr> <tr><td> swL2McastFilterPortMaxGroupTable</td><td></td></tr> <tr><td> swL2McastFilterPortMaxGroupEntry</td><td></td></tr> <tr><td> swL2McastFilterPortMaxGroupPortIndex</td><td></td></tr> <tr><td> swL2McastFilterPortMaxGroup</td><td></td></tr> <tr><td> swL2McastFilterPortInfoTable</td><td></td></tr> <tr><td> swL2McastFilterPortInfoEntry</td><td></td></tr> <tr><td> swL2McastFilterPortInfoPortIndex</td><td></td></tr> <tr><td> swL2McastFilterPortInfoProfileName</td><td></td></tr> </table>	swL2MultiFilter		swL2McastFilterTable		swL2McastFilterEntry		swL2McastFilterProfileIndex		swL2McastFilterProfileName		swL2McastFilterAddOrDelState		swL2McastFilterGroupList		swL2McastFilterStatus		swL2McastFilterPortTable		swL2McastFilterPortEntry		swL2McastFilterPortGroupPortIndex		swL2McastFilterPortProfileAddOrDelState		swL2McastFilterPortProfileID		swL2McastFilterPortMaxGroupTable		swL2McastFilterPortMaxGroupEntry		swL2McastFilterPortMaxGroupPortIndex		swL2McastFilterPortMaxGroup		swL2McastFilterPortInfoTable		swL2McastFilterPortInfoEntry		swL2McastFilterPortInfoPortIndex		swL2McastFilterPortInfoProfileName		<p>Object name: swL2McastFilterPortInfoProfileName Object ID: 1.3.6.1.4.1.171.11.63.6.2.22.5.1.2 Module: DES3028-L2MGMT-MIB</p> <p>Base syntax: Octet String Composed syntax: DisplayString Access: Read-Only Status: Current</p> <p>Parent node: swL2McastFilterPortInfoEntry First child: None Description: The multicast filter address profile Name.</p>
swL2MultiFilter																																											
swL2McastFilterTable																																											
swL2McastFilterEntry																																											
swL2McastFilterProfileIndex																																											
swL2McastFilterProfileName																																											
swL2McastFilterAddOrDelState																																											
swL2McastFilterGroupList																																											
swL2McastFilterStatus																																											
swL2McastFilterPortTable																																											
swL2McastFilterPortEntry																																											
swL2McastFilterPortGroupPortIndex																																											
swL2McastFilterPortProfileAddOrDelState																																											
swL2McastFilterPortProfileID																																											
swL2McastFilterPortMaxGroupTable																																											
swL2McastFilterPortMaxGroupEntry																																											
swL2McastFilterPortMaxGroupPortIndex																																											
swL2McastFilterPortMaxGroup																																											
swL2McastFilterPortInfoTable																																											
swL2McastFilterPortInfoEntry																																											
swL2McastFilterPortInfoPortIndex																																											
swL2McastFilterPortInfoProfileName																																											