

How to set up the FDB entry via SNMP in DES-3200-28?

[Topology]:

Comp1 ---- (port 9) **DES-3200-28**(192.168.0.1/24)

Firmware :1.33B05

Comp1 MAC: 00-07-E9-39-2D-15 / IP: 192.168.0.221

MAC address change to decimal=**0.7.233.57.45.21**

[Configuration]:

```
snmpset -v 2c -c private 192.168.0.1 1.3.6.1.2.1.17.7.1.3.1.1.3.1.0.7.233.57.45.21.0 x
0x00800000 1.3.6.1.2.1.17.7.1.3.1.1.4.1.0.7.233.57.45.21.0 i 3
SNMPv2-SMI::mib-2.17.7.1.3.1.1.3.1.0.7.233.57.45.21.0 = Hex-STRING: 00 80 00 00
SNMPv2-SMI::mib-2.17.7.1.3.1.1.4.1.0.7.233.57.45.21.0 = INTEGER: 3
```

DES-3200-28:5#sh fdb

Command: show fdb

Unicast MAC Address Aging Time = 300

VID	VLAN	Name	MAC Address	Port	Type
1	default	00-07-E9-39-2D-15	9	Permanent	
1	default	00-1E-58-6F-34-E0	CPU	Self	

Total Entries : 2