


## How to save configuration with SNMP command on DGS-3627 v2.50b25

Follow the command below to save active configuration to NV-RAM

```
#snmpset -v 2c -c private 192.168.1.24 1.3.6.1.4.1.171.12.1.2.18.4.0 i  
2
```

Please refer the following the description for file save OID



<b>Object name</b>	agentBscFileSystemSaveCfg
<b>Object ID</b>	1.3.6.1.4.1.171.12.1.2.18.4
<b>Module</b>	AGENT-GENERAL-MIB
<b>Base syntax</b>	Integer
<b>Composed syntax</b>	INTEGER
<b>Access</b>	Read-Write
<b>Status</b>	Current
<b>Value list</b>	1 : other(1) 2 : cfg(2) 3 : log(3) 4 : all(4)
<b>Parent node</b>	agentBscFileSystemMgmt
<b>First child</b>	None
<b>Description</b>	This indicates the method of saving information to the NV-RAM of the other(1) - none of the following. cfg(2) - save configuration. log(3) - save log. all(4) - save both ( active configuration and log).